

# Setting Multiple Start Times Your Hunter Pro-C, ICC, or X-Core Irrigation Controller

1. Turn dial to PROGRAM START TIMES. Display will show OFF or show the 1<sup>st</sup> start time already set to turn the program on.
2. Push the plus ( + ) or minus ( - ) button to adjust the time to desired 1<sup>st</sup> start time. Ideally, this is early morning, before the sun has risen.
  - The time adjusts in 15-minute increments.
  - Pay attention to whether you are setting for AM or PM.
3. Add a 2<sup>nd</sup> start time by pushing right arrow (→).
  - Display will show “2<sup>nd</sup> OFF”, add or turn on the 2<sup>nd</sup> start time by pushing plus ( + ) or minus ( - ). This can be approximately 2 hours after the first start time (i.e. 12am and 2am).
4. Pushing right arrow (→) again will bring up the 3<sup>rd</sup> and 4<sup>th</sup> start times. Generally, these aren’t needed except in areas with very steep slopes or establishing a new landscape. Keep them OFF.
5. Turn dial back to RUN. This will allow the controller to start running the schedule you’ve set. You can also turn the dial to SYSTEM OFF to keep the irrigation turned off until you want it to run. Having it on OFF does not erase what you’ve just programmed.

